




Door/Window Sensor


Securifi SZ-DWS04 Micro Door / Window Sensor

Instant Alerts




Receive smartphone alerts if any door or window is opened

Peace of Mind




Protect what is important to you (e.g. Wine Cellar, Safe closet)

Security



Know when and where a potential breach has occurred

Automation



Turn lights automatically when you open a door

Product Description

Compatible with ZigBee Products	Easy, Low-Cost Installation with Adhesive Tapes or Screws
Small, Modest Design for Any Location	Built-in Tamper Switch for Additional protection
Up to 3-Year Battery Life with One Replaceable Lithium CR2032	Radio Frequency: 2.4GHz
RF Communication Range: 300M (Open Air)	ZigBee Channel: 11, 14, 15, 19, 20, 24, 25
Switch: Tamper Switch / Reset x 1	LED Indicator: Green LED x 1
RF Supervision Interval: 24 Mins	Battery: CR2032 x 1
Average Battery Life: 3 Years (20 triggers/day)	Adjustable Sensitivity Interval 4 - 10m
ZigBee Profile: HA1.2, ZigBee: Built-in Ember ZigBee Module	Temperature Sensor Accuracy : +/- 2 degree
Dimensions (H x W x L) Main Unit : 7.4mm x 26mm x 51mm (0.29" x 1.02" x 2")	Dimensions (H x W x L) Magnet Unit : 7.4mm x 15.5mm x 28.3mm (0.29" x 0.61" x 1.11")
Compliance: FCC, ETL (UL634)	Operation Temperature: 0° - 40°C (32° - 104°F); Humidity: 10% - 80% RH (non-condensing)
Ordering Information: SZ-DWS04: ZigBee Micro Door / Window Sensor	Storage Temperature: -20° - 60°C (-4° - 140°F); Humidity: -20% - 60% RH (non-condensing)



Securifi Ltd.
+886-2-2726-0100
sales@securifi.com
<http://www.securifi.com>